- Step 5 Align the PCI or PCIe card with the slot, and press the card into the slot until it is firmly seated.
- Step 6 Close the top cover back to the chassis and fasten all screws.



IPC922-215-FL Quick Installation Guide

Checklist

✓ IPC922-215-FL System Unit x 1	✓ Driver CD x 1
✓ Wall Mount Bracket x 2	✓ Quick Manual x 1
✓ Food Pad x 4	✓ Screw Pack x 1
✓ BTX Cable 2P for Remote SW Cable x 1	✓ HD Bracket x 1

Note: Please contact your local vendors if any damaged or missing items. DO NOT apply power to the board if there is any damaged component.

Installing the Memory Module

- **Step 1** Turn off the system, and disconnect the power connector.
- Step 2 Loosen screws to remove the top cover from the chassis.
- **Step 3** Please follow steps below to install the memory module:
 - Align the memory module with the socket that notches of memory module must match the socket keys for a correct installation.
 - Install the memory module into the socket and push it firmly down until it is fully seated. The socket latches are clipped on to the edges of the SO-DIMM.





INSERTING MODULE

MODULE FULLY SEATED

9416G922020E

©Copyright 2016 Axiomtek Co., Ltd.

Version A1 January 2016

Printed in Taiwan

9416G922020E
©Copyright 2016 Axiomtek Co., Ltd.
Version A1 January 2016
Printed in Taiwan

Installing the Hard Disk Drive

- **Step 1** Turn off the system, and disconnect the power connector.
- Step 2 Loosen screws to remove the top cover from the chassis.
- Step 3 Open the top cover and locate the Hard Disk Drive from the side. Use assembly parts to fix HDD with the bracket.





HDD LOCATION

ASSEMBLING HDD BRACKET

Step 4 Install and fix the HDD through the bottom, next, plug the power cable in HDD





HDD FIXED

Installing the PCI or PCIe Card

- **Step 1** Turn off the system.
- **Step 2** Disconnect the power connector.
- Step 3 Loosen screws to remove the top cover from the chassis. Removing the PCI or PCIe bracket by releasing the button as marked.



Step 4 Locate the PCI or PCIe slots from the top.

